

7. How to Contact ProAVM

For all enquiries write to:-

ProAVM
61 Station Road
Irthlingborough
Northants
NN9 5QE
United Kingdom

Or telephone 01933 650 700 within the UK, +44 1933 650 700 from outside the UK.

Or fax 01933 650 726 within the UK, +44 1933 650 726 from outside the UK.

Or email sales@proavm.com for sales enquiries or technical.support@proavm.com for technical support.

Alternatively visit our web site: <http://www.proavm.com>

8. Declaration of Conformity

Name of Manufacturer: ProAVM
Address of Manufacturer: 61 Station Road
Irthlingborough
Northants
NN9 5QE

Product: MATCH-IT2 Dual Stereo Matching Unit - Dual Replay

Declaration: The product described above complies with the requirements of the Low Voltage Directive (73/23/EEC) and the protection requirements of the EMC Directive (89/336/EEC) issued by the Commission of the European Community.

Compliance with these directives implies conformity to the following European Standards:

EN 60065:1993	Safety requirements for mains operated electronic and related apparatus for household and similar general use
EN 55103-1:1997	Electromagnetic compatibility - Product family standard for audio, video, audiovisual and entertainment lighting control apparatus for professional use (emissions - environmental categories E1 to E5)
EN 55103-2:1997	Electromagnetic compatibility - Product family standard for audio, video, audiovisual and entertainment lighting control apparatus for professional use (immunity - environmental categories E1 to E5)

9. Warranty

This product is shipped with a 5 year return to base warranty. Please return the product to the company that you bought it from.

No part of this manual may be reproduced or transmitted in any form or by any means, electronic or mechanical, including photocopying, recording or information storage and retrieval systems, for any purpose other than the purchaser's personal use, without the express written permission of ProAVM.

Information in this document is subject to change without notice and does not represent a commitment on the part of ProAVM. ProAVM shall not be liable for any direct, indirect, consequential or incidental damages as a result of the use or misuse of this equipment, handbook or any related materials.



MATCH-IT2 Dual Stereo Matching Unit - Dual Replay

V1.00 © ProAVM 2006

1. Introduction

The ProAVM MATCH-IT2 translates the low-level, unbalanced signals used by domestic and semi-professional equipment to the more robust, balanced format used in the professional environment. It is therefore the ideal solution to the common studio problem of interfacing inexpensive source units to professional mixing consoles and other balanced equipment.

With the ever-increasing density of equipment in the modern studio, proper balancing of signals is vital if sources are to be kept free of noise and interference. The MATCH-IT2 provides dual unidirectional stereo matching for two domestic/semi-professional playback machines, and its wide gain range includes 0dB for higher level unbalanced sources such as some CD players.

For matching of record/replay (bidirectional) sources, see the ProAVM MATCH-IT.

The MATCH-IT2 is housed in a compact and robust metal case with mounting holes for wall or under desk mounting. An optional 1U rackmounting kit, RACK-IT, is available from ProAVM dealers.

2. Safety & Electrical Hazard

This unit contains high voltages which could be fatal. YOU MUST ALWAYS ISOLATE THE UNIT FROM THE MAINS SUPPLY BY COMPLETELY DISCONNECTING IT BEFORE ATTEMPTING TO OPEN THE CASE.

THIS EQUIPMENT MUST BE EARTHED.

Do not expose this equipment to rain or any other source of water.

In common with all mains operated equipment, only suitably trained competent personnel should attempt to adjust, modify or repair this equipment or operate it with the cover removed. In case of query please contact your local agent or ProAVM. Any unauthorised adjustment, modification or repair of this equipment may invalidate any warranty and/or safety approvals that apply.

Please read all of this manual and familiarise yourself with the controls before attempting to use this equipment. To ensure safety, it is the responsibility of the user to install and operate this equipment in a manner that is within the manufacturers specifications.

3. Unpacking The Equipment

This package should contain, in addition to this manual:

1 x MATCH-IT2
1 x IEC Mains lead

If any items are missing or damaged please inform your supplier immediately.
Ensure that the MATCH-IT2 has been supplied for the correct mains/line voltage for your country.

4. Controls and Connectors

Unbalanced Inputs	RCA female phono connectors. Centre Pin Signal Shell Ground
Balanced Outputs	3 pin male XLR, electronically balanced. Outputs may be unbalanced without affecting gain by linking pins 1 and 3. Pin 1 Ground Pin 2 Hot (Phase) Pin 3 Cold (Non-phase)
Balanced Output Gain	Individual multiturn adjustments for channel gain. Nominal gain range 0 to +25dB.
Power LED	Lights continuously to confirm correct operation of power supply.
Mains Fuse	20mm antisurge mains fuse. 100mA(T) for 230V units 250mA(T) for 115V units DISCONNECT MAINS BEFORE ATTEMPTING TO CHANGE FUSE.
Mains	IEC male connector.

5. Operation

Refer to section 4 for a description of the controls and connectors.

The MATCH-IT2 is designed to integrate easily into a wide variety of systems. The outputs will operate balanced or unbalanced without problems, and the wide range of gain available can accommodate disparate signal levels.

Connections

Input

Refer to section 4 of this manual for the pin connections of the input female RCA sockets. To achieve specified performance, leads should be of quality screened cable and not exceed 1m in length.

Output

Refer to section 4 of this manual for the pin connections of the output male XLR sockets. For unbalanced use, connect pin 3 to pin 1 and take the signal from pin 2, with pin 1/3 as ground. To achieve specified performance, leads should be of quality screened cable.

Output Gain

Apply the expected input signal level to the MATCH-IT2. Monitor the output and adjust the gain control (clockwise to increase gain) to give the level required.

6. Specifications

Inputs	Unbalanced, 22kohm input impedance
Maximum input level	+24dBu
Outputs	Electronically balanced
Maximum output level	+24dBu (10kS), +23.5dBu (600ohm)
Nominal gain range	0dB to +25dB
Noise	< -80dB (RMS, 20Hz-22kHz, +14dB gain)
Harmonic distortion	<0.01% (100Hz-10kHz)
Crosstalk	< -80dB (L-R & A-B, 1kHz, +14dB gain)
AF response	<±0.1dB (20Hz-20kHz)
Power supply	115 or 230VAC (factory set)
Power consumption	6VA
Inrush current	<0.5A
Dimensions (excluding & connectors)	294mm x 114mm x 44mm
Fixing centres	4 x 5mm hole on 276mm x 74mm rectangle
Weight	0.8kg unpacked, 1.0kg packed